




STATIC TRANSFER SWITCHES 1- and 3- PHASE



English









STS - STATIC TRANSFER SWITCHES BROCHURE

YOUR CRITICAL POWER SOLUTION PARTNER.

The Borri Group has been developing and building uninterruptible power systems since 1932 and is a global provider of power electronics systems and solutions for harsh industrial and demanding critical power requirements.

Borri's R&D vast expertise in all facets of firmware, power electronics and mechanical design provides innovative solutions for tomorrows problems in Industrial and Critical Power applications.

The company prides itself on its first-class service and superior engineering disciplines. To ensure sustained quality, Borri manages all its processes in house from feed studies to design, production and after sales service technology. Based in Bibbiena, Italy with over 15,000 m² production area, Borri operates across all five continents with subsidiaries in USA, Canada, Germany, UAE, India and Malaysia.

It has also established a strong distributor network, able to deliver on site support and technical guidance indicative of our own capabilities.







Critical Power Solutions

Designing and building mission critical UPS's 1- and 3-Phase up to 21 MW.



Industrial Power Solutions

Designing, engineering and building customised AC and DC power supply systems for harsh industrial applications.



Service

Borri team of experts support you to the highest standards no matter where you are in the world.





5

STATIC TRANSFER SWITCHES 1- and 3-PHASE

STS

from 16 A _____ to 3000 A

0.000





Short circuit protection

Ensuring maximum source protection in dual feed applications.

No break seamless transfers

Automatically transferring loads to alternative power sources when the primary power source fails or is not available.

High availability

Thanks to source separation, dual maintenance bypass and redundant crititical paths.

1-Phase and 3-Phase static transfer switches for seamless load transfer in dual path power systems. The STS rugged design and high reliability provides supply redundancy and prevents fault propagation.



1-PHASE STATIC TRANSFER SWITCHES

STS 16-32

from 16 A — to 32 A





STS 16 rear view



STS 32 rear view

1-phase static transfer switch series designed to offer solutions for the protection of single-phase loads.

Features and benefits

- Dual redundant power supplies to control boards, for increased availability.
- Redundant cooling and fan failure monitoring, for reliable operation.
- Real-time SCR fault sensing, preventing fault propagation.
- High overload capability, for robust electrical design.


- ITS maintenance switch, for hot swap maintainability.
- Compact 19" rack system design, for easy integration.
- LCD/LED display, providing user friendly interface.
- Comprehensive set of communication options for total remote monitoring of equipment operation.
- **Main options**
- ITS maintenance switch.
- RS485 ModBus interface.
- SNMP interface.

ITS maintenance switch main features

- 16 A and 32 A version.
- 6 x 40 A input terminal board.
- Zero switching time.



STS block diagram





STS 16 - STS 32 technical data

Model	STS 16	STS 32			
Rating (A)	16	32			
Dimensions WxDxH (mm)	440x275x88				
Weight (kg)	8	9			
Input					
Connection type	Hardwired 5w				
Nominal voltage	200/208/220/230/240 Vac 1-phase				
Voltage tolerance	± 5% (up to ±20%)				
Absolute maximum voltage range	150 Vac to 300 Vac				
Frequency and range	50/60 Hz, ± 5% (up to ±20%)				
Source harmonic voltage content	Unlimited				
Transfer phase angle	5° to 20°				
Output					
Connection type	8 IEC-C 13, hardwired 3w	Hardwired 3w			
Nominal voltage	200/208/220/230/240 Vac 1-phase				
Frequency	50/60 Hz				
Transfer time	2 to 6 ms				
Transfer mode	Break before make, transfer inhibit on fault				
Load power factor	1 to 0.3				
Maximum crest factor	3:1				
THD current feedback from load	Unlimited				
Overload capacity	125% for 1 min, 150% for 30 s, 200% for 5 s				
Efficiency (AC/AC)	99	%			
Connectivity and function extensions					
Front panel	Graphical LCD display				
Remote communication	Included: RS-232 ModBus, USB, voltage free relay contacts; Optional: one slot for SNMP adapter or RS-485 ModBus adapter				
System					
Protection degree	IP 20				
Colour	RAL 9005				
Installation layout	Rack mounted				
Accessibilty	Front and rear				

Other features

invironmental				
Operating temperature range	-5°C to +40°C			
Storage temperature range	-10°C to +70°C			
Altitude (AMSL)	< 1000 m without power reduction, > 1000 m with reduction of 0.5% per 100 m			
Audible noise at 1 m (dBA)	< 60			
Standards and certifications				
Quality assurance, environment, health and safety	ISO 9001:2015, ISO 14001:2015, BS OHSAS 18001:2007			
Safety	IEC 60950-1			
EMC	EN 55022, EN 55024			
Transfer voltage limit	IEEE Standard 446			
Protection degree	IEC 60529			
Performance	IEC/EN 62310-3			
Marking	CE			




3-PHASE STATIC TRANSFER SWITCHES

STS 300

3-phase centralised static transfer switch series designed to offer solutions for the protection of loads even in harsh environment.



STS block diagram





Dry contact relay card (Included)

To send UPS status to PLC's, SCADA's or AS400's by voltage free SPDT contacts



- Continuous monitoring of voltage and frequency and automatic instant (<4 ms) transfers for secure power switching without cross connection between sources.
- Short circuit transfer inhibit for robust load protection.
- SCR fault detection and backfeed protection for maximum upstream safety.
- Dual manual bypass for complete source independence during maintenance.
- True oversized neutral (2x In), redundant cooling with monitored fans and redundant (3x3) internal power supply in

all system control boards for top product reliability in high availability applications.

- Full front access for easy maintenance.
- Bottom and top cable entry for maximum installation versatility.
- Comprehensive set of communication options for total remote monitoring of equipment operation.
- Fully compliance with all international product standards for maximum quality guarantee.
- Circuit breakers for reliable and safe tripping on all operating conditions.

Main options

- Isolation transformer.
- Plug-in breakers.
- Output distribution panels.
- Panel builder version.
- Additional SPDT contact relay board.
- 4-pole configuration.
- Operation without neutral.



RS485 ModBus-RTU port (Included)

To send UPS status to BMS's by RS485 connection and ModBus-RTU protocol. For remote monitoring and remote service



STS 300 technical data

Rating (A)*	100	250	400	630	800	1000	1250
Dimensions WxDxH (mm)**	820x835x1475		1220x860x1900		2000×1000×2100		
Weight (kg)**	265	290	305	615	660	1000	1450
nput			•			· · · · ·	
Connection type	Hardwired 4w						
Nominal voltage	208/380/400/415/440/480 Vac 3-phase with neutral						
Voltage tolerance	±10% (up to ±20% on request)						
Frequency and range	50/60 Hz, ±2 Hz (up to ±4 Hz on request)						
Source harmonic voltage content	Unlimited (if THD>20% transfer time ≤10ms)						
Transfer phase angle	5° to 30°						
Dutput							
Connection type	Hardwired 4w						
Nominal voltage	208/380/400/415/440/480 Vac 3-phase with neutral						
Frequency	50/60 Hz						
Transfer time	≤4 ms						
Transfer mode	Break before make, transfer inhibit on fault						
Load power factor	1 to 0.3						
Maximum crest factor				3:1			
THD current feedback from load	Unlimited						
Overload capacity***	125% for 30 min, 150% for 10 min, 200% for 30 s, 2000% for 1 cycle, 4000% for ½ cycle						
Efficiency (AC/AC)	>99%						
Connectivity and function extensions							
Front panel	Graphical LCD display, mimic LED panel and keyboard						
Remote communication	Included: dry contact relay card, RS232 and RS485 serial ports, ModBus-RTU protocol. Optional: additional dry contact relay card						
Optional function extensions	4-pole configuration; plug-in circuit breakers; operation without neutral; panel builder execution; output distribution panels; isolation transformer						
System							
Protection degree	IP 20 (other options)						
Colour	RAL 9005 (other options)						
Installation layout	Wall, back to back and side by side installation allowed						
Accessibilty	Front access, bottom and top cable entry						

*rating up to 3000 A on request **3-pole version *** conditions apply

Other features

Environmental				
Operating temperature range	0°C to +40°C			
Storage temperature range	-10°C to +70°C			
Altitude (AMSL)	< 1000 m without power reduction, > 1000 m with reduction of 0.5% per 100 m			
Audible noise at 1 m (dBA)	<62			
Standards and certifications				
Quality assurance, environment, health and safety	ISO 9001:2015, ISO 14001:2015, BS OHSAS 18001:2007			
Safety	IEC/EN 62310-1			
EMC	IEC/EN 62310-2			
Breakers	IEC/EN60947-3			
Transfer voltage limits	IEEE Standard 446			
Protection degree	IEC 60529			
Performance	IEC/EN 62310-3			
Marking	CE			



SERVICE

Customer's expectation defines Borri's priority from the early analysis of the project requirements to a worldwide commissioning and service. Many thousands of systems have been successfully installed and maintained globally, with continuous support from a highly trained team of expert, certified technicians and engineers. From the professional set-up of Borri's training centre or on site, the training and service team stand ready to provide support and contribute to tailored training at Borri or on site. You can be assured of Borri support to the highest standards no matter where in the world you are.

नकररा



Planning, installation, commissioning

Borri assist you in every single step of your project. Our R&D team can analyse and develop solutions to a wide range of edge system requirements.

START SMULATION



Analytical tests

Borri undertakes a series of analytical tests in order to guarantee higher efficiency and continuity to your system operation.



Repair & spare parts

All spare parts supplied by Borri are original, tested and guaranteed to be fully compliant with Borri solutions.



Remote monitoring

Guardian Net remote monitoring system allows you to detect any deviation from optimum operation and trigger proper and immediate response, so that anomalies don't evolve into issues.



Maintenance

Preventive maintenance guarantees uninterrupted operations and optimised system efficiency.



Battery tests

Batteries have a limited time life and their proper maintenance is of high importance to guarantee efficiency to the UPS and avoid potential failures. Borri delivers high quality and performing batteries to assure smooth operations.



Training

Borri offers distributors and customers a service training structured in 3 levels. Courses can be held in Borri training centres or on-site.







13



Since 1932, securing your power with passion and commitment.



Extract from OMG60326revC | 07-2022 Due to our policy of continuous development, data in this document is subject to change without notice and becomes contractual only after written confirmation



www.borri.it

BORRI HEADQUARTERS AND FACTORY

Borri S.p.A

Via 8 Marzo, 2 52011 Bibbiena (AR) Italy Tel. +39 0575 5351 Fax +39 0575 561811 info.borri.it@legrand.com

BORRI SUBSIDIARIES AND SERVICE CENTRES

Americas

Borri Power (US) Inc.

9000 Clay Road, Suit 104 Houston, Texas, 77080

USA Tel. +1 346 212 2686 Fax +1 346 980 8875 info.borripower@legrand.com

Asia Pacific

Borri Asia Pacific Engineering Sdn. Bhd.

No.13, Jalan Serendah 26/41, Sekitar 26, Seksyen 26, 40400 Shah Alam, Selangor Malaysia Tel. +60 3 5191 9098 Fax +60 3 5103 8728 sales@borri-asia.com

India

Borri Power India Pvt. Ltd.

Plot No. 69, Ground Floor Nagarjuna Hills, Panjagutta Hyderabad, 500 082 India Tel. +91 40 2335 4095 info.borri.it@legrand.com

Middle East and Africa

Borri Power Middle East FZCO

1-151, Techno Hub PO Box: 342036 Dubai Silicon Oasis, Dubai UAE Tel. +971 4 3200528 Fax +971 4 3200529 info.borri.it@legrand.com